RGB BLINDER: 2 EYE

1. 2-eye 3-in-1 point control DMX Channel menu AH60 DH61

10-channel mode (A001 status)

channel	function	explain
CH1	Total dimming	Total dimming, from dark to bright
CH2	1eye R dimming	1eye R dimming, from dark to bright
CH3	1eye G dimming	1eye G dimming, from dark to bright
CH4	1eye B dimming	1eye B dimming, from dark to bright
CH5	2eye R dimming	2eye R dimming, from dark to bright
CH6	2eye G dimming	2eye G dimming, from dark to bright
CH7	2eye B dimming	2eye B dimming, from dark to bright
CH8	Total stroboscopic	Global stroboscopic, from slow to fast
CH9	Function selection	0：Dimming mode；1——62：Color selection (selected by ch10)；63—124：Jump change；125—186：Gradual change；187—249:Pulse change;250-255:Voice control (ch10 selects voice control 1 and 2)
CH10	Function speed	Function speed, from slow to fast (color selection for color output, voice control strobe and jump for voice control)

10-channel mode（d001）

channel	function	explain
CH1	Total dimming	Total dimming, from dark to bright
CH2	Total stroboscopic	Global stroboscopic, from slow to fast
CH3	Function selection	0：Dimming mode；1——62：Color selection (selected by ch4)；63—124：Jump change；125—186：Gradual change；187—249:Pulse change;250-255:Voice control (ch4 selects voice control 1 and 2)
CH4	Function speed	Function speed, from slow to fast (color selection for color output, voice control strobe and jump for voice control)
CH5	1eye R dimming	1eye R dimming, from dark to bright
CH6	1eye G dimming	1eye G dimming, from dark to bright
CH7	1eye B dimming	1eye B dimming, from dark to bright
CH8	2eye R dimming	2eye R dimming, from dark to bright
CH9	2eye G dimming	2eye G dimming, from dark to bright
CH10	2eye B dimming	2eye B dimming, from dark to bright

Nixie tube display menu description

NUM	content	Numerical range	Function and description
1	A001	001- 512	DMX512 address code setting - 10 channel mode
2	d001	001- 512	DMX512 address code setting - 10 channel mode
3	r255	000 - 255	1eye R dimming, from dark to bright.
4	G255	000 - 255	1eye G dimming, from dark to bright.
5	b255	000 - 255	1eye B dimming, from dark to bright.
6	u255	000 - 255	2eye R dimming, from dark to bright.
7	y255	000 - 255	2eye G dimming, from dark to bright.
8	P255	000 - 255	2eye B dimming, from dark to bright.
9	FH99	01 - 99	Stroboscopic, speed from slow to fast.
10	CL01	01 - 62	Manual color selection mode.
11	CC99	01 - 99	Jump from slow to fast.。

12	DE99	01 - 99	Gradient, from slow to fast.
13	CP99	01 - 99	Pulse changes from slow to fast.
14	SU01	01 - 02	Mode: 1 is stroboscopic jump, 2 is jump

3 Master slave descriptions

In D001 or A001 state, the slave signal is automatically received without additional setting.

Input voltage: AC90-240V 50HZ/60HZ

Casing material: profile + metal

Power: 190-200W

Light source: 2 pcs100W COB lamp beads

Luminous color: positive white/warm white / two-color / RGB can be selected

Luminous angle:35°

Control mode: DMX / master-slave / voice control

Channel: 6/10/11ch channel

Color temperature: 3200K or 5600k or RGB