Waterproof face light

WHITE & WARM WHITE

user's guide

Please read through this lamp before using it

catalogue

一、Unboxing to check the..... 02 pages

二、Product Introduction..... 02 pages

三、Product parameter..... 02 pages

四、The interface shows the..... 02 pages

五、Operation and description of the..... Page 03

6. Channel Table..... 05 pages

7, common fault analysis and fault troubleshootingscheme..... 06 pages

Viii. Notes:..... 06 pages

IX. Statement of..... 06 pages

First of all, thank you for choosing your products. Please read this instruction manual carefully and completely, and keep it properly for reference in use.

First, open the box inspection

When receiving the product, please carefully take and put it, check whether the product has any damage caused by transportation, and check the following accessories: lamps- - - - - - - - - -4 sets / box manual warranty card- - - - - - - - - - -1 copy

二、product presentation

This lamp is made of new cast aluminum shell, beautiful shape, smooth, fully reflect the characteristics of modern lamp products. The products are designed and produced in strict accordance with CE standards, and fully conform to the international standard DMX512 protocol. They can be controlled by a single station or used by each other, and can adapt to photography, photography, TV stations and other strict lighting requirements.

1. Power: 200W
2.LED beads: 460 w cob beads
3. Lens angle: conventional 25°
4. Color temperature: 3000K-6000K
5. Strobe: random strobe, beating in order, strobe effect (random strobe, beating in order, strobe effect)
6. Heat dissipation: completely cooled by convection through the heat sink
7. Novel design of aluminum casting shell, high-strength tempered glass, streamlined appearance design
8. Control mode: DMX-512 control operation, master-slave mode, single-machine mode, and voice control mode
9. Display: LED digital tube button dial code
10. Waterproof grade: IP65
11. channel:8CH

12. Integrated dimming: 0-100%
13. Strobe: electronic strobe 1-25 fps / s
14. Product size: 240x220x245mm
15. Weight: 4.3 kg

four. Interface display

1 2 3 4

1. The MENU menu
2. UP value
3. DOWN, with decreasing values
4. ENTER Confirmation

五、Operation and description:

MENU	UP	DOWN	Increase the range value	function declaration	ENTER
A001	Use the UP or DOWN keys.		A001 ↕ AS12	Set the address code	The ENTER key confirms and saves the current value.
FF01			FF01 ↕ FF50	Various colors change randomly, the larger the	
CC01			CC01 ↕ CC50	Various colors flash randomly, the larger the	
bEbE			bEbE	Sound control mode	
Sr01			Sr01 ↕ Sr50	The color is all bright (white light) flashing	
dE00			dE00	Various colors change randomly	
r000			r000 ↕ r255	Red dimming.000~255 The larger the value, the greater	

MENU	UP	DOWN	Increase the range value	function declaration	ENTER
G000	Use the UP or DOWN keys.		G000 ↕ G255	Green dimming.000~255 The larger the value, the greater the brightness.	The ENTER key confirms and saves the current value.
b000			b000 ↕ b255	Blue dimming.000~255 The larger the value, the greater the brightness.	
U000			U000 ↕ U255	White dimming.000~255 The larger the value, the greater the brightness.	
Y000			Y000 ↕ Y255	Yellow dimming.000~255 The larger the value, the greater the brightness.	

Vi. Channel Table:

order number	function	explain
Channel 1	Total dimming	Linear dimming, from dark to bright 000-255
Channel 2	stroboflash	Strobe speed of 000-255
Channel 3	Is white	Dimmming, linear dimming, from dark to bright 000-255
Channel 4	Is white	Dimmming, linear dimming, from dark to bright 000-255
Channel 5	Warm white	Dimmming, linear dimming, from dark to bright 000-255
Channel 6	Warm white	Dimmming, linear dimming, from dark to bright 000-255
Channel 7	Color temperature change	0—255
Channel 8	Functional speed	Functional speed, from slow to fast 000-255

Seven, the common fault analysis and fault troubleshooting scheme

fault phenomenon	failure cause	processing method
1. The display screen of the lamp is not bright, and	1. Whether the power supply is normal	① Correct access to the power supply

the fan does not operate	**2. Whether the line is correct**	
2. A lamp is not controlled by the signal	**1. The address code is correct** **2. Whether the signal line is well connected**	**① Set the correct address code** **② Connect the signal line correctly**
3. A lamp or a few color lamp beads are not bright	**1. One of the lamp beads may burn out**	**① renewal**

VIII. Notes:

The installation and debugging shall be carried out by professional personnel

The surface of the lamps should not be wiped with dilute solvents such as alcohol

The ambient temperature of lamps should not exceed 40℃, away from fire and flammable items, do not let water wet the lamps

The crane must be equipped with a lamp hook and safety rope that can carry the 10 times the weight of the lamp itself

This lamp shall be kept dry to avoid working in a wet environment.

9. Statement

This product in the factory, the performance is intact, complete packaging. All users shall strictly observe the warnings and operating instructions stated above, any damage caused by misuse is not covered by the Company's warranty and the failure and problems caused by the neglect of the operating manual.