

4 EYE COB- RGBW WATERPROOF



user's guide

Please read this lamp before using it

catalogue

**1、 U n b o x i n g t o c h e c k
the..... 02 pages**

**2、 P r o d u c t
Introduction..... 02 pages**

**3、 Product parameter.....
0 2 p a g e s**

**4、 T h e i n t e r f a c e s h o w s
the..... 02 pages**

**5、 O p e r a t i o n a n d d e s c r i p t i o n o f
the..... 03 pages**

6. Channel Table.....

0 5 p a g e s

**7, common fault analysis and fault troubleshooting
scheme..... 06 pages**

Viii. Notes:..... 06

p a g e s

IX. Statement of.....

0 6 p a g e s

First of all, thank you for choosing your products. Please read this instruction manual carefully and completely, and keep it properly for reference in use.

1. OOBA

**When receiving the product, please carefully take and put it, check whether the product has any damage caused by transportation, and check the following accessories: lamps- - - - -
--4 sets / box manual warranty card- - - - -1 copy**

2、 product presentation

This lamp is made of new cast aluminum shell, beautiful shape, smooth, fully reflect the characteristics of modern lamp products. The products are designed and produced in strict accordance with CE standards, fully in line with the international standard DMX512 protocol, which can be controlled by a single station or controlled by each other, and can adapt to photography, photography, TV stations and other strict lighting occasions.

3. Product technical parameters: 1. Power: 200W

2.LED beads: 450 w cob beads (RGBW)

3. Lens angle: conventional 15°

4. Color: RGBW

5. Strobe: random strobe, beating in order, strobe effect (random strobe, beating in order, strobe effect)

6. Heat dissipation: completely cooled by convection through the heat sink

7. Novel design of aluminum casting shell, high-strength tempered glass, streamlined appearance design

8. Control mode: DMX-512 control operation, master-slave mode, stand-alone mode, and voice control mode

9. Display: LED digital tube button dial code

10. Waterproof grade: IP65

11. channel:8CH

12. Integrated dimming: 0-100%

13. Strobe: electronic strobe 1-25 fps / s

14. Product size: 240x220x245mm

15. Weight: 4.3 kg

four. Interface display



decreasing values

1 2 3 4

1. The MENU menu

2. UP value

3. DOWN, with

4. ENTER Confirmation

5、Operation and description:

MENU	UP	DOWN	Increase the range value	function declaration	ENTER
	Use the UP or DOWN keys.		 ↑↓ 	Set the address code	The ENTER key confirms and saves the current value.
			 ↑↓ 	Various colors change randomly, the larger the 01~50 value, the	
			 ↑↓ 	Various colors flash randomly, the larger the 01~50	
				Sound control mode	
			 ↑↓ 	The color is all bright (white light) flashing	
				Various colors change randomly	
			 ↑↓ 	Red dimming.000~255 The larger the value, the greater	

MENU	UP	DOWN	Increase the range value	function declaration	ENTER
	Use the UP or DOWN keys.		 ↑↓ 	Green dimming.000~255 The larger the value, the greater the brightness.	The ENTER key confirms and saves the current value.
			 ↑↓ 	Blue dimming.000~255 The larger the value, the greater the brightness.	
			 ↑↓ 	White dimming.000~255 The larger the value, the greater the brightness.	
			 ↑↓ 	Yellow dimming.000~255 The larger the value, the greater the brightness.	

Vi. Channel Table:

order number	function	explain
Channel 1	Total dimming	Linear dimming, from dark to bright 000-255
Channel 2	red	Dimmming, linear dimming, from dark to bright 000-255
Channel 3	hispid arthraxon	Dimmming, linear dimming, from dark to bright 000-255
Channel 4	blue	Dimmming, linear dimming, from dark to bright 000-255
Channel 5	white	Dimmming, linear dimming, from dark to bright 000-255
Channel 6	strobflash	Strobe speed of 000-255
Channel 7	Color temperature change	0—255
Channel 8	Functional speed	Functional speed, from slow to fast 000-255

Seven, the common fault analysis and fault troubleshooting scheme

fault phenomenon	failure cause	processing method
1. The display screen of the lamp is not bright, and the fan does not operate	1. Whether the power supply is normal 2. Whether the line is correct	① Correctly access to the power supply
2. A lamp is not controlled by the signal	1. The address code is correct 2. Whether the signal line is well connected	① Set the correct address code ② Connect the signal line correctly
3. A lamp or a few color lamp beads are not bright	1. One of the lamp beads may burn out	① renewal

VIII. Notes:

The installation and debugging shall be carried out by professional personnel

The surface of the lamps should not be wiped with dilute solvents such as alcohol

The ambient temperature of lamps should not exceed 40°C, away from fire and flammable items, do not let water wet the lamps

The hanging installation must be equipped with a lamp hook and a safety rope that can carry 10 times the weight of the lamp itself

This lamp shall be kept dry to avoid working in a wet environment.

9. Statement

This product in the factory, the performance of the intact, complete packaging. All users shall strictly observe the warnings and operating instructions stated above, any damage caused by misuse is not under the Company's warranty, and the neglect of the operating manual.